DSL-N13

802.11n Wireless ADSL2/2+ Modem Router

- with Asus AiDisk FTP server applications, *plus* "Quick setup" - smart auto-detection of local ADSL settings!
- 11n technology for more throughput and data rate. Fast & Guaranteed multi-media content streaming.

Spezifikationen

LAN Ports	■ Support: Both Ethernet and 802.3 with Max. Bit Rate 10/100 Mbps with auto cross-over function (MDI-X) ■ Connector: RJ45 for 10/100 BaseT
ADSL Features	■ Support: ITU G.992.1/G.992.3/ G.992.5 dmt AnnexA ANSI T1.413 issue 2 ■ Connector: RJ11 phone jack
Antenna	3 external dipole antennas; support diversity
USB port	2 x USB 2.0
EZS button	Push for 5 seconds to enter easy setup mode
Reset Button	Push for above 5 seconds to restore factory settings
LED Indicator	Power, LAN x 4, ADSL, IP, USB, AIR
Management	Web-based manager UPnP Internet Gateway Device UPnP Media Server.
Firewall	NAT and SPI. Can built extra one firewall to protect Internet traffic and another one for wireless
Power	AC Input: 100V~240V(50~60HZ); DC Output: 12V with max. 1.25A current
Emission	ETS; CE Mark; FCC Part 15
Operating Frequency	2.4 - 2.5 GHz
Data Rate	Draft 802.11n: up to 300Mbps 802.11g: 6, 9, 12, 18, 24, 36, 48, 54Mbps 802.11b: 1, 2, 5.5, 11Mbps *Note: Actual throughput will vary depending on the wireless environment and other parameters
Operating Channels	11 for N. America, 14 Japan, 13 Europe (ETSI), 3 (non-overlapping)
Range	Indoor 130 ft (40 m), outdoor (LOS, Light-Of-Sight) 2000 ft (600 m) at 11Mbps. Indoor 80 ft (25 m), outdoor (LOS, Light-Of-Sight) 500 ft (150 m) at 54Mbps. *The range may vary by different environment
Encryption	64/128-bit WEP TKIP, AES, WPA, WPA-PSK
Authentication	MAC address, 802.1x

USB Applications	Printer Server, FTP Server

*The product (electrical , electronic equipment, Mercury-containing button cell battery) should not be placed in municipal waste. Check local regulations for disposal of electronic products.
*All specifications are subject to change without notice. Plese check with your supplier for exact offers. Products may not be available in all markets.
*PCB color and bundle software versions are subject to change without notice.
*Brand and product names mentioned are trademarks of their respective companies.